

## A VEHICLE INCLUDING A THREE-PHASE GENERATOR

### RELATED APPLICATIONS

This application claims the benefit of prior filed co-pending U.S. Patent  
5 Application No. 09/835,889, entitled A SMALL ENGINE VEHICLE INCLUDING A  
GENERATOR, filed on April 16, 2001.

### BACKGROUND OF THE INVENTION

The invention relates to a vehicle including a generator and, particularly, to a  
vehicle including a generator having a plurality of wires disposed on a stator core in a  
10 three-phase winding arrangement.

Small mobile generators are capable of providing a stable 120-volts root-mean-  
square (VRMS), 60 hertz (Hz) power source. In addition, because the generators are  
mobile, the generators may be transported to the desired location where electrical power is  
needed. However, mobile generators are usually placed on a trailer and pulled to the  
15 desired location by a vehicle.

Small-engine vehicles, such as riding lawn mowers, tractors, all-terrain vehicles  
(ATV's), golf carts, etc., are robust vehicles capable of travelling to remote locations.  
Small-engine vehicles are also able to pull small mobile generators. However, when the  
desired location for the generator is in a remote location or across a treacherous landscape,  
20 it may be difficult for the small-engine vehicle to pull the trailer carrying the generator to  
the desired location.

When an operator owns a small-engine vehicle and a mobile generator, the  
operator's costs increase. In addition, the operator is required to maintain two pieces of  
machinery (e.g., maintain two engines). This may not be practical when the mobile  
25 generator is infrequently used.

### SUMMARY OF THE INVENTION

The invention provides a vehicle including a plurality of wheels, an internal  
combustion engine having a drive shaft interconnected to drive at least one of the wheels,

a stator having a core, a plurality of wires disposed on the core in a three-phase winding arrangement, and a flywheel-rotor apparatus. The flywheel-rotor apparatus surrounds at least a portion of the stator and has an aperture that receives the drive shaft. The flywheel-rotor apparatus is operable to magnetically interact with the stator to produce a three-phase alternating current in the wires, and provides inertia to the internal combustion engine. The vehicle further includes power circuitry electrically connected to the wires. The power circuitry receives the three-phase alternating current and controllably generates a single-phase alternating current.

The stator, the plurality of wires, the flywheel-rotor apparatus, and the power circuitry form a generator. The vehicle of the present invention utilizes a three-phase winding arrangement because the power rating for a three-phase generator is typically greater than the power rating for a single-phase stator generator having the same weight. Other features, advantages and embodiments of the invention are set forth in the following detailed description, drawings and claims.

## BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a schematic diagram of a vehicle embodying the invention.

Fig. 2 is a partial side view of an engine and generator combination embodying the invention.

Fig. 3 is a partial perspective view of a stator and engine housing shown in Fig. 2.

Fig. 4 is a front plan view of a first stator.

Fig. 5 is a rear plan view of the first stator.

Fig. 6 is a rear plan view of a second stator.

Fig. 7 is a rear plan view of a third stator.

Fig. 8 is a rear plan view of a fourth stator.

Fig. 8A is a cross-sectional side view of the stator taken along line 8A-8A in Fig. 8.

Fig. 9 is a schematic representation of a stator-winding scheme.

Fig. 10 is a rear plan view of a flywheel-rotor apparatus.

Fig. 11 is a cross-sectional side view of the flywheel-rotor apparatus taken along line 11-11 in Fig. 10.

Fig. 12 is a schematic diagram of power circuitry schematically shown in Fig. 1.

Fig. 13 is an electrical schematic of a regulator schematically shown in Fig. 12.

5 Fig. 14 is an electrical schematic of a bridge circuit schematically shown in Fig. 12.

Fig. 15 is an electrical schematic of a first driver circuit schematically shown in Fig. 12.

Fig. 16 is an electrical schematic of a second driver circuit schematically shown in Fig. 12.

10 Fig. 17 is an electrical schematic of a current limit circuit schematically shown in Fig. 12.

Fig. 18 is an electrical schematic of a microprocessor, a voltage feedback circuit, a thermal shutdown circuit, and a voltage regulator schematically shown in Fig. 12.

Fig. 19 is a flow chart of a software program.

15 Figs. 20(a) and 20(b) are flowcharts of an interrupt service step shown in Fig. 19.

Fig. 21 is a first electrical schematic of a generator having a three-phase winding arrangement.

Fig. 22 is a second electrical schematic of a generator having a three-phase winding arrangement.

20 Fig. 23 is a third electrical schematic of a generator having a three-phase winding arrangement.

Fig. 24 is a fourth electrical schematic of a generator having a three-phase winding arrangement.

25 Fig. 25 is a fifth electrical schematic of a generator having a three-phase winding arrangement.

Before any embodiments of the invention are explained in full detail, it is to be understood that the invention is not limited in its application to the details of construction and the arrangement of components set forth in the following description or illustrated in the following drawings. The invention is capable of other embodiments and of being practiced or of being carried out in various ways. Also, it is to be understood that the phraseology and terminology used herein is for the purpose of description and should not be regarded as limiting. The use of "having," "including" and "comprising" and variations thereof herein is meant to encompass the items listed thereafter and equivalents thereof as well as additional items.

## 10 DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

A vehicle 100 embodying the invention is schematically shown in Fig. 1. The vehicle 100 includes a plurality of wheels 105 and an internal combustion engine 110 (hereinafter referred to as "engine") interconnected to drive at least one of the wheels 105. That is, the engine 110 (also shown in Fig. 2) produces mechanical power causing a shaft 115 to rotate. One or more wheels 105 are interconnected with the rotating shaft 115 causing the interconnected wheels 105 to rotate. For the embodiment described herein, the vehicle 100 is a riding lawnmower with a Briggs & Stratton, Inc. INTEK™ or QUANTUM™ engine. However, the vehicle 100 may be any vehicle including an engine (e.g., a tractor, a lawnmower, an ATV, a golf cart, a motorcycle, etc.)

The vehicle 100 further includes an alternator or generator 120 interconnected with the engine 110. In general, the generator 120 includes a flywheel-rotor apparatus 125 (Fig. 2), a stator (e.g., stator 130, Fig. 2), power circuitry 135 (Fig. 1) and an electrical outlet 140 (Fig. 1). As best shown in Fig. 2 and shown in partial perspective view Fig. 3, the engine includes a housing 145, and the stator (e.g., stator 130) is interconnected (e.g., mounted) to the housing 145 by one or more fasteners (discussed below). Multiple embodiments of the stator 130 are shown in Figs. 3-8. As will become apparent below, other stators are possible.

With reference to Figs. 3, 4 and 5, the stator 130 includes a magnetically permeable stator core 150, which is of generally cylindrical shape. The core 150 is preferably formed by a plurality of stacked laminations 155 (best shown in Fig. 3) mechanically

interconnected together by one or more fasteners 160. Alternatively, in other embodiments, the core 150 is a solid core formed by one magnetically permeable member, or is magnetic powdered material compressed to form the core 150. The one or more fasteners 160 may include rivets, bolts, latches, etc., or even an epoxy or glue. In the  
5 embodiment shown, the core 150 includes a first plurality of laminations 165 (best shown in Figs. 3 and 5) and a second plurality of laminations 170 (best shown in Figs. 3 and 5) fastened by four rivets 160 (best shown in Fig. 3).

The stator 130 includes a central opening 175 having a longitudinal axis 180 (best shown in Figs. 4 and 5). The stator 130 is mounted on the engine housing 145 such that  
10 the central opening 175 receives at least a portion of the shaft 115. The stator 130 is secured to the housing 145 by one or more fasteners (e.g., rivet, bolt, latch, epoxy, glue, etc.) 185.

The stator core 150 forms at least one inner surface at least partially surrounding the longitudinal axis 180. For the embodiment shown and with reference to Fig. 5, the  
15 first plurality of laminations 165 form a first inner surface 190 surrounding the longitudinal axis 180, and the second plurality of laminations 170 form a second inner surface 195 that extends in the circumferential direction with respect to the longitudinal axis 180. The second inner surface 195 is adjacent to the first inner surface 190 in the axial direction. The first plurality of laminations 165 further includes first, second, third  
20 and fourth shelves 215, 220, 225 and 230, and first, second, third and fourth apertures 235, 240, 245 and 250. The first shelf 215 and a portion of the second inner surface 195 partially define a first recess 255, the second shelf 220 and a portion of the second inner surface 195 partially define a second recess 260, the third shelf 225 and a portion of the second inner surface 195 partially define a third recess 265, and the fourth shelf 230 and a  
25 portion of the second inner surface 195 partially define a fourth recess 270.

The recesses 255, 260, 265 and 270 result in a volume of the stator core 150 that is "removed" as compared to a core that has only one plurality of substantially similarly designed laminations of cylindrical shape (discussed further below). The creation of the recesses 255, 260, 265 and 270 allows the recesses 255, 260, 265 and 270 to extend in the  
30 circumferential direction for receiving a portion of the housing 145. By creating the

recesses 255, 260, 265 and 270, the stator 130 may be retrofitted on existing engines 110 where space is an issue.

For example, the housing 145 of a prior art engine may include a structure that would otherwise result in interference (e.g., rib structures 275 as shown in Fig. 3). In addition, the amount of engine compartment volume of the vehicle (i.e., the space "under the hood") may be of concern. In order to mount the generator 120 within the existing volume, the recesses 255, 260, 265 and 270 may be created in the stator 130. The recesses 255, 260, 265 and 270 allow one or more structures to extend into the one or more recesses 255, 260, 265 and 270 (e.g., the rib structures 275 shown in Fig. 3 extend into the one or more recesses 255, 260, 265 and 270.) This allows the stator 130 to sit closer to the engine 110 than if no recess was created.

Furthermore, one or more apertures 235, 240, 245 or 250 may extend through recesses 255, 260, 265 and 270, respectively, in the longitudinal direction. The apertures allow the stator 130 to be mounted closer to the engine housing 145. Having the stator 130 sit closer to the engine housing 145 allows for the engine and generator combination to be more compact and fit within an existing engine compartment volume of an existing vehicle.

In another embodiment, the stator core 276 (shown in Fig. 6) does not include one or more recesses. For this embodiment, space is not an issue. Rather, the stator 130 of this embodiment uses a "cylindrical" stator core 276 that generates more power than a core having at least one recess (e.g., a core 150 shown in Fig. 5).

In another embodiment, the second plurality of laminations partially defines one recess 277 that completely surrounds the longitudinal axis (shown in Fig. 7). In addition, for other embodiments, the number of recesses may vary and the amount of volume of a recess may vary.

In another embodiment, the recess 278 (shown in Fig. 8) is formed by at least three sets of laminations 279A, 279B and 279C. Specifically, the recess 278 is formed by gradually varying the radius R1, R2 and R3 of at least a portion of each set of laminations in the axial direction. For another embodiment, the one or more recesses may be defined

by a solid core. For some solid core embodiments, the one or more recesses are defined by a continuously varying radius in the longitudinal direction.

As best shown in Fig. 3, the stator 130 further includes a plurality of radially-extending teeth 280 and insulators 295 and 300 disposed on the teeth 280. The teeth 280 receive one or more electrical wires 305 that surround the insulators 295 and 300. The insulators 295 and 300 electrically isolate the wires 305 from the stator core 150. For the embodiment shown, the insulators 295 and 300 are first and second plastic insulators disposed on the core 150. Furthermore, for the embodiment's shown in Figs. 2-9, the number of teeth, which may be represented by the number (x), is equal to eighteen and the number of wires 305 is equal to two. However, the number of teeth may vary and the number of wires may vary. For example, in another embodiment, the number of teeth is equal to twenty. Increasing the number of teeth enables more power to be generated.

As best shown in Fig. 5, the teeth 280 (Fig. 3) are numbered from 1 to (x) (e.g., 1 to 18). As schematically shown in Fig. 9, a first wire 310 is wound around a first plurality of teeth to form a first plurality of coils 315. The first plurality of coils 315 create a first plurality of magnetic poles that interact with a plurality of magnets (discussed below) of the flywheel-rotor apparatus 125. A second wire 320 is wound around a second plurality of teeth to form a second plurality of coils 325. The second plurality of coils 325 create a second plurality of magnetic poles that interact with the plurality of magnets (discussed below) of the flywheel-rotor apparatus 125.

Specifically, for the embodiment schematically shown in Fig. 9, the core 150 includes a plurality of teeth numbered from 1 to 18. The first wire 310 is wound on the core 150 to form a first group of coils 315. The first group of coils 315 forms sixteen poles numbered 1 to 16 with each pole being formed on a respective tooth 1 to 16. The first wire 310 includes first and second ends 330 and 335 that exit the core between two adjacent teeth receiving the first group of coils 315. For the embodiment shown, the first and second ends 330 and 335 exit the core between the first and second teeth. The second wire 320 is disposed on the core 150 to form a second group of coils 325. The second group of coils 325 forms two poles numbered 17 and 18 with each pole being formed on a respective tooth 17 and 18. The second wire 320 includes third and fourth ends 340 and

345 that exit the core between two adjacent teeth receiving the second group of coils 325. For the embodiment shown, the third and fourth ends 340 and 345 exit the core between the seventeenth and eighteenth teeth.

Although the first group of coils 315 form a first group of poles 1 to 16 and the second group of coils 325 form a second group of poles 17 and 18, the number of poles of each group may vary. For example, the first group of poles may be numbered from one to  $(x - n)$  where  $(x)$  is the total number of poles or teeth and  $(n)$  is the number of poles in the second group. For the second group, the poles are numbered from  $(x - n + 1)$  to  $(x)$ . Thus, for the embodiment shown,  $(x)$  is eighteen and  $(n)$  is two. In another embodiment,  $(x)$  is twenty and  $(n)$  is two.

As will be discussed in further detail below, the flywheel-rotor apparatus 125 magnetically interacts with the stator 130 to generate a first voltage in the first wire 310 and generates a second voltage in the second wire 320, where the first voltage is greater than the second voltage. For example, the first voltage may be greater than approximately 200 V peak-to-peak, and the second voltage may be less than approximately 50 V peak-to-peak. The RMS voltage (and power) generated in each wire 310 or 320 is determined in part by the number of poles formed by the respective group of coils. In other words, varying the number of poles in a group of coils varies the voltage generated by the group of coils. For example, varying the number of poles for the first group of coils 315 from sixteen to eighteen increases the voltage generated by the first group of coils 315. Thus, depending on the voltage required by a group of coils, the number of poles (and teeth) may vary.

In addition, varying the number of turns of each coil also increases the RMS voltage generated by the group of coils. For example, if the number of turns for each coil changes from fifteen to twenty, then a higher voltage is generated for the group of coils.

For the winding scheme shown, the first and second ends 330 and 335 exit between two adjacent teeth receiving the first group of coils 315 (e.g., between teeth 1 and 2), and the third and fourth ends 340 and 345 exit between two adjacent teeth receiving the second group of coils 325 (e.g., between teeth 17 and 18). One reason for this is that undesirable noise is transmitted from the first and second ends to the third and fourth ends due to the

first group of coils generating a much higher voltage than the second group of coils. By having the first and second ends exit between two teeth of the first group of coils and by having the third and fourth ends exit between two teeth of the second group of coils, the noise is reduced. Although the embodiment described herein has the first and second ends exit between the first and second teeth, the first and second ends may exit between two other adjacent teeth receiving the first group of coils. Similarly, if the number of teeth receiving the second group of coils varies (e.g.,  $(n)$  is equal to 4), then the third and fourth ends may exit between any two adjacent teeth receiving the second group of coils. However, if noise is not a concern, then other winding schemes may be used for the vehicle.

As shown in Fig. 9, the coils forming the odd numbered poles of the first group (e.g., poles 1, 3, 5, 7, 9, 11, 13, 15) are wound in a first direction (e.g., counterclockwise when viewing the core 150 from the rear), and the coils forming the even numbered poles of the first group (e.g., poles 2, 4, 6, 8, 10, 12, 14, 16) are wound in a second direction (e.g., counterclockwise when viewing the core 150 from the rear). The second direction is different than the first direction. Similarly, the coils forming the odd numbered poles of the second group (e.g., pole 17) are wound in the first direction, and the coils forming the even numbered poles of the second group (e.g., pole 18) are wound in the second direction.

One method of disposing the first and second wires 310 and 320 on the stator 130 is as follows. As schematically shown in Fig. 9, the first wire 310 is wound on the core 150 to form the first group of coils 315. The first group of coils 315 is formed by placing the first end 310 between teeth 1 and 2 and winding the wire around tooth 1 in the first direction. Next, the wire 310 is then wound to tooth 2 and a second coil is wound around tooth 2 in the second direction. The wire 310 then proceeds to tooth 3 and is wound around tooth 3 in the first direction. Next, the wire proceeds to tooth 4 and is wound around tooth 4 in the second direction. The winding on the first group of coils 315 is wound similarly for the remaining teeth 6-16, where the odd number poles are wound in the first direction and the even number of poles are wound in the second direction.

After winding the first wire 310 around tooth 16, the second wire 320 is cut to form the second end 330. An insulator 350 (e.g., a "shrink-tube" insulator) (Fig. 3) is disposed around the second end 330 and the first wire 310 is interwound back to tooth 2. That is, the first wire 310 is wound for a half turn around tooth 16, proceeds to the tooth 15, and is wound a half turn around tooth 15 (Fig. 9). The first wire 310 is wound for half turns around the remaining teeth back to tooth 2 and exits between teeth 1 and 2. The insulator 350 protects the half-turn winding from short-circuiting with the coils of the respective teeth. For example, the half-turn winding around tooth 7 does not short circuit with the coil that forms pole 7. The first and second ends 330 and 335 exit between the teeth 1 and 2 receiving the first and second coils. To strain relieve the first and second ends 330 and 335, an epoxy 355 (Fig. 5) may be applied to ends 330 and 335.

Similar to the first wire 310, the second wire 320 having third and fourth ends 340 and 345 is disposed on the core 150 to form the second group of coils 325. The second group of coils is formed by placing the third end 340 between tooth 17 and winding the wire around tooth 17 in the first direction. Next, the second wire 320 is then wound to tooth 18 and a second coil is wound around tooth 18 in the second direction. After winding the second wire 320 around tooth 18, the second wire 320 is cut to form the fourth end 345. The third and fourth ends 340 and 345 then exit between teeth 17 and 18. To strain relieve the third and fourth ends 340 and 345, an epoxy 360 (Fig. 5) may be applied to ends 340 and 345.

For the embodiment shown in Figs. 4-9, (n) is equal to two. However, if (n) is greater than two, then the winding scheme for the second wire 320 may be similar to the winding scheme for the first wire 310.

Referring back to Fig. 2, the generator 120 further includes a flywheel-rotor apparatus 125 that is coaxially aligned with the stator 130. As best shown in Figs. 10 and 11, the flywheel-rotor apparatus 125 includes a first central opening 370 for receiving the drive shaft 115 (Fig. 2). When the drive shaft 115 rotates, the flywheel-rotor apparatus 125 also rotates. The rotating flywheel-rotor apparatus 125 induces a magnetic field within the stator 130 causing a current to be generated in each wire 310 and 320.

Referring again to Figs. 10 and 11, the flywheel-rotor apparatus 125 includes a third inner surface 375 that at least partially surrounds the stator 130. The flywheel-rotor apparatus 125 further includes a plurality of rotor magnets 380 (e.g., eighteen magnets) mounted by fasteners (e.g., an epoxy or glue) to the third inner surface 375. In the  
5 embodiment show, the rotor magnets 380 are neodymium-iron-boron (NdFeB) magnets. The flywheel-rotor apparatus 125 further includes an ignition magnet 385 mounted in the exterior of the flywheel-rotor apparatus 125 for generating an ignition signal, gearing teeth 390 disposed in the exterior of the flywheel-rotor apparatus 125 for interconnecting the flywheel-rotor apparatus 125 to an engine starting motor, apertures 395 for receiving a fan  
10 plate having fins for cooling the engine and generator, and one or more balancing holes 400 used for balancing the flywheel-rotor apparatus 125.

The flywheel-rotor apparatus 125 includes a flywheel portion 402 interconnected with a rotor portion 404. The rotor portion 404 includes the magnets 380 and a back-iron 405. The rotor portion 404 is external to the stator 130 and magnetically interacts with the  
15 stator 130. The flywheel portion 402 is an additional mass formed integral with the rotor portion 404 and may include a portion of the rotor back-iron 405. The flywheel portion 404 evens out the rotation of the drive shaft 115 while the engine 110 is running. The additional mass of the flywheel portion 402 is necessary for the internal-combustion engine 110 to operate properly and the rotor portion 404 is necessary to produce the  
20 magnetic field for the generator 120. By combining the flywheel and rotor portions 402 and 404 into one apparatus 125, the number of parts is reduced and the amount of space required for the engine/generator combination 110 and 120 is reduced.

Referring back to Figs. 1 and 2, the generator 120 includes the power circuitry 135. The power circuitry 135 includes a first power circuitry and a second power circuitry,  
25 which may be interconnected. In general, the first power circuitry receives a current and generates a single-phase alternating current (e.g., a 120-VRMS, 60-Hz signal), and the second power circuitry receives a current and generates a direct current. Fig. 12 shows a schematic diagram for one embodiment of the first power circuitry 450, and Figs. 13-18 show the electrical schematic of the first power circuitry 450. As will become more  
30 apparent below, other embodiments of the power circuitry 135 may be used with the generator 120.

With reference to Figs. 12 and 13, the first power circuitry 450 includes a regulator 500. The regulator 500 receives a high-voltage, alternating-current (AC) input, and rectifies and regulates the received alternating current to generate a low-voltage DC output and a high-voltage DC output. The high-voltage, AC input is received at terminals W3 and W9 from first and second ends 330 and 335. For the embodiment shown in Figs. 12 and 13, the low-voltage DC output is approximately 15 VDC and the high-voltage DC output is approximately 150 VDC. However, in other embodiments, the low-voltage and high-voltage DC output voltages varies. Even further, for some embodiments, the high-voltage DC signal varies depending on the load attached to the power circuitry 135.

The high-voltage AC input may be a single-phase AC input generated using the above-described stator and winding arrangement, may be a single-phase AC input generated using another stator and winding arrangement, or a three-phase AC input generated using a three-phase winding arrangement. Unless specified otherwise, the description below with reference to Figs. 12-18 is for a single-phase AC input produced using the above-described stator and winding arrangement.

With reference to Fig. 13, the rectifier/regulator 500 includes a bridge rectifier 505. The bridge rectifier includes diodes D5 and D14 forming the upper portion of the bridge rectifier 505, and silicon-controlled rectifiers SCR1 and SCR3 forming the lower portion of the bridge rectifier 505. Diodes D4 and D15 provide an input or control signal for controlling the bridge rectifier 505. First filter 510 (resistor R29 and capacitor C4) filters the control signal provided to silicon-controlled rectifier SCR1 and second filter 515 (resistor R19 and capacitor C29) filters the control signal provided to silicon-control rectifier SCR2. Filtering the control signals provided to the silicon-controlled rectifiers SCR1 and SCR2 prevents the silicon-controlled rectifiers SCR1 and SCR2 from being too sensitive. During operation of the bridge rectifier 505, the rectifier 505 receives the high-voltage AC input generated by the stator 130 via inputs W9 and W3, rectifies and regulates the AC input in response to the control signals being provided to the silicon-controlled rectifiers SCR1 and SCR3, and provides a high-voltage DC output. The high-voltage DC output is stored on capacitors C6 and C3, which act as a DC bus. For the embodiment described, the high-voltage DC output is preferably 150 VDC. But, depending on the load attached to the first power circuitry 450, the DC bus may fluctuate

between 100 VDC and 150 VDC. If the stator 130 is a three-phase stator, then the bridge rectifier includes input W4, diode D7, silicon-control rectifier SCR2, and third filter 520 (resistor R30 and capacitor C5).

5 The rectifier/regulator 500 further includes a voltage monitor 525 and a trigger circuit 530. The voltage monitor 525 includes opto-isolator U2, precision voltage reference U1, zener diode D9 and resistors R28, R31 and R32. The trigger circuit 530 includes zener diodes D1 and D2, metal-oxide semiconductor field-effect transistors (MOSFETs) Q1 and Q2, opto-isolator U8, diac Q11, capacitors C1 and C2, and resistors R2, R3, R4, R5, R6, R8, R9, R10 and R27. The voltage monitor 525 and the trigger  
10 circuit 530 control the bridge rectifier 505 to provide a continuous bus voltage between, 130 VDC and 150 VDC. Specifically, the trigger circuit 530 acts as a phase control that activates the silicon-control rectifiers SCR1 and SCR3 depending on the amount of power required to be added to the DC bus. For example, if the voltage monitor 525 senses a voltage on the DC bus greater than 150 VDC, then the trigger circuit 530 triggers the  
15 silicon-controlled rectifiers SCR1 and SCR3 later in the phase of the high-voltage AC input. This results in less energy being provided to the DC bus and, therefore, a lower voltage. Similarly, if the voltage monitor 525 senses a voltage on the DC bus less than 150 VDC, then the trigger circuit 530 causes the silicon-controlled rectifiers SCR1 and SCR3 to activate sooner in the phase of the high-voltage AC input. This results in more  
20 energy being provided to the DC bus and, consequently, a higher voltage. The voltage monitor 525 and the trigger circuit 530 attempt to regulate the DC bus voltage to approximately 150 VDC. However, depending on the load attached to the first power circuitry 450, the DC bus voltage may range between 130 VDC and 150 VDC. Of course, other voltages may be used for the DC bus.

25 The rectifier/regulator 500 further includes a low-voltage DC power supply 535. The low-voltage DC power supply 535 includes zener diode D10, capacitor C7 and resistors R33 and R34. The low-voltage DC power supply 535 receives the high-voltage DC output and produces a low-voltage DC output. For example, the low-voltage DC signal may be 15 VDC. Of course, other low-voltage DC outputs may be used.

Referring back to Fig. 12, the first power circuitry 450 further includes a bridge circuit 540. For the embodiment shown (Fig. 14), the bridge circuit 540 is an H-bridge circuit. The bridge circuit 540 includes first branch 545 (MOSFETs Q9, Q10 and Q14, resistor bridge 42, and resistor R22), second branch 550 (MOSFETs Q7, Q8, and Q15, resistor bridge R20, and resistor R25), third branch 555 (MOSFETs Q5, Q6, and Q12, resistor bridge R21, and resistor R14), and fourth branch 560 (MOSFETs Q3, Q4, and Q13, resistor bridge R13, and resistor R18). The bridge circuit 540 receives the high-voltage DC bus, and produces a 120-VRMS, 60-Hz AC output at terminals W1 and W2 in response to a plurality of drive signals 1aOUT, 1bOUT, 2aOUT and 2bOUT. Of course, other output voltages and frequencies (e.g., a 100-VRMS, 50-Hz AC output) may be produced. In addition, other bridge circuits may be used. For example, the embodiment shown in Fig. 14 has three MOSFETs in each branch. For a different embodiment, the number of MOSFETs may vary (e.g., two MOSFETs) depending on the capacity of the MOSFETs and the maximum expected current generated by the bridge circuit 540.

The drive signals 1aOUT, 1bOUT, 2aOUT and 2bOUT, and floating ground signals 1aSOURCE and 2aSOURCE are provided to the bridge circuit 540 by driver circuits 565 and 570 (Figs. 12, 15 and 16). First driver circuit 565 (Fig. 15) includes driver U5, capacitors C14, C15, C16, C17, C18, resistors R44, R50 and R51, and diode D12. The first drive circuit 565 drives the first and second branches 545 and 550 (Fig. 14) with the signals 1aOUT, 1bOUT and 1aSOURCE in response to gate signals GATE1a and GATE1b (discussed below). The second drive circuit 570 includes driver U4, capacitors C9, C10, C11, C12, C13, resistors R41, R52 and R53, and diode D11. The second drive circuit 570 (Fig. 16) drives the third and fourth branches 555 and 560 with the signals 2aOUT, 2bOUT and 2aSOURCE in response to the signals GATE2a and GATE2b (discussed below).

During operation of the bridge circuit 540 and the first and second driver circuits 565 and 570, an output signal is generated at terminals W1 and W2 (Fig. 14). The output is a pulse-width-modulated (PWM) signal having a frequency of approximately sixty Hz and a voltage of approximately 120 VRMS. Specifically, the first and second drivers 565 and 570 drive the MOSFETs Q3, Q4, Q5, Q6, Q7, Q8, Q9, Q10, Q12, Q13, Q14 and Q15, to produce a PWM 120-VRMS, 60-Hz signal at W1, W2. Each cycle includes a square

5 wave that is PWM to produce the required RMS voltage. The width of each half cycle is widened or narrowed depending on the DC bus voltage. If the DC bus voltage is low, then the width of each half cycle is widened. Conversely, if the DC bus voltage is high, then the width of the half cycle is narrowed. Thus, based on the drive signals provided to the bridge circuit 540, the output of the bridge circuit 540 maintains a relatively constant 120-VRMS, 60-Hz signal at outputs W1 and W2.

10 The output signals 1aOUT, 1bOUT, 1aSOURCE, 2aOUT, 2bOUT, and 2aSOURCE result from gate signals GATE1a, GATE1b, GATE2a and GATE2b. The GATE signals GATE1a, GATE1b, GATE2a, and GATE2b are generated by a microprocessor (discussed below). The first and second drivers U4 and U5 translate the gate signals GATE1a, GATE1b, GATE2a and GATE2b to 15-VDC drive signals (i.e., 1aOUT, 1bOUT, 2aOUT and 2bOUT). The 15-VDC drive signals are necessary to drive the MOSFETs Q3, Q4, Q5, Q6, Q7, Q8, Q9, Q10, Q12, Q13, Q14 and Q15. The signals 1aSOURCE and 2aSOURCE provide a floating reference to the bridge circuit 540.

15 The bridge circuit 540 shown in Fig. 14 includes a shunt resistor R11. The shunt resistor R11 is a power shunt for measuring the output current of the bridge circuit 540. The shunt resistor R11 is used to determine if an overload current is present i.e., if an operator is applying too large of a load to the bridge circuit 540. If too large of a load is present, the microprocessor (discussed below) narrows the pulse width of the 120-VRMS, 60-Hz output so that it cannot deliver too large of a current through the bridge circuit 540. The current measurement signal SHUNT is provided to a current limit circuit 575 (shown in Fig. 17). The current limit circuit 575 includes operational amplifiers U3A, U3B, resistors R1, R35, R36, R37, R38, R39, and R40, and capacitors C8 and C26. The operational amplifiers U3A amplifies the signal SHUNT, and the operational amplifier 25 U3B acts as a comparator between a reference signal and the amplified SHUNT signal. The reference signal is formed by resistors R39 and R40. The reference signal is set such that the peak current created by the bridge circuit cannot exceed a maximum peak current (e.g., forty-five amps). The maximum peak current is the maximum safe current the MOSFETs Q3, Q4, Q5, Q6, Q7, Q8, Q9, Q10, Q12, Q13, Q14 and Q15 can handle 30 without burning out. The current limit signal iLIMIT is provided to the microprocessor (discussed below).

As shown in Figs. 12 and 18, the first power circuitry 450 includes microprocessor U7. The microprocessor U7 receives and executes a software program from memory. Based on the inputs provided to the microprocessor U7, the microprocessor controls the driver circuits 565 and 570 with gate signals GATE1a, GATE1b, GATE2a and GATE2b. Specifically, the software determines the pulse width of each half cycle generated by the bridge circuit 540 based on the inputs provided to the microprocessor U7. For example, one of the input signals is the current limit signal iLIMIT. If the signal iLIMIT signifies that the current to the load is excessive, the microprocessor U7 controllably reduces the width of the PWM output signal.

As shown in Figs. 12 and 18, the first power circuitry 450 further includes a voltage feedback circuit 580. The voltage feedback circuit 580 includes resistors R48 and R49 and capacitor C23. The voltage feedback circuit 580 reduces the voltage from the DC bus to a 0-VDC to 5-VDC signal. The feedback from the DC bus informs the microprocessor U7 what the DC voltage is on the high-voltage bus.

As shown in Figs. 12 and 18, the first power circuitry 450 further includes a thermal shut down circuit 585. The thermal shut down circuit 585 includes a thermistor R15, a capacitor C24 and a resistor R12. The thermistor R15 is mounted near the MOSFETs Q3, Q4, Q5, Q6, Q7, Q8, Q9, Q10, Q12, Q13, Q14 and Q15, and senses the temperature generated by the bridge circuit 540. If the bridge circuit 540 generates an excessive temperature, thermistor R15 conducts and generates a high-logic signal TRIP. The microprocessor U7 receives the high-logic signal TRIP and stops producing the 120-VRMS, 60-Hz output. An example temperature may be 90-100 degrees Celsius. The higher the temperature gets, the sooner the thermal shut down circuit 585 generates the high-logic signal TRIP.

As shown in Figs. 12 and 18, the first power circuitry 450 further includes an oscillator XT1 for providing an oscillating signal to the microprocessor U7 and a voltage regulator U9 for generating a 5-VDC VCC signal. The first power circuitry 450 further includes a deactivate circuit 590 including resistors R63 and R64, capacitors C25 and C27 and optoisolator U6. The deactivate circuit 590 receives a 12-VDC blade signal 12BLADE or a 12-VDC input signal from terminals W7 and W8. When no twelve-volt

signal is present, the microprocessor U7 prevents the 120-VRMS, 60-Hz signal from being generated. Alternatively, if the 12-VDC signal is present then the first power circuitry 450 may generate an output. For example, if the generator 110 is mounted on a lawnmower, then the 12-BLADE signal informs the microprocessor U7 whether the blade is running.

- 5 If the blade is rotating, the first power circuitry 450 does not produce an output.

As shown in Figs. 12 and 18, inputs W5 and W6 receive a signal from a power switch. The power switch is an on/off switch that the operator activates and deactivates for controlling the first power circuitry 450. In the embodiment described herein, the power switch has to be turned ON from the OFF position in order for the power circuitry 135 to generate any power. For example, if an operator turns the engine on while the power switch is already in the ON position, then the microprocessor U7 does not allow an output from the power circuitry 135. This prevents an accidental output from being generated. In order to enable the power circuitry 135, the switch must be moved to the OFF position and then returned to the ON position.

15 Having described multiple embodiments of a vehicle 100 including a generator 120, the operation of the vehicle 100 will be discussed below. In operation, when an operator starts the vehicle 100, the engine 110 causes the drive shaft 115 to rotate and, consequently, the flywheel/rotor apparatus 125 to rotate. The flywheel/rotor apparatus 125 uses its inertia to smooth-out the rotation of the drive shaft 115. This allows the engine to run evenly for driving the rotation of the wheels 105. In addition, the magnetic fields produced by the rotor magnets 380 interact with the stator resulting in a current being generated in the first and second wires 310 and 320. The current produced in the second wire 320 is provided to the second power circuitry for powering the engine ignition system and/or the engine battery, and the current produced in the first wire 310 is provided to the first power circuitry 450. The current that is provided to the first power circuitry 450 is first regulated to produce a high-voltage DC output and a low voltage-DC output. The high-voltage DC output is stored in a storage device (e.g., capacitors C3 and C6). The storage device acts as a DC bus voltage. The low-voltage DC signal is provided to, among other things, the VCC regulator for generating a five-volt VCC signal. The 5-VDC VCC signal is provided to the microprocessor U7.

When the microprocessor U7 receives the 5-VDC VCC signal, the microprocessor U7 loads a software program from memory into the microprocessor U7. As shown in Fig. 19 and at step 710, the software initializes the microprocessor U7 and sets one or more interrupts. The initializing of the software includes initializing a main timer and setting an error flag ERR to high. The error flag ERR remains high until the software validates everything is properly running. The interrupts include a periodic interrupt (e.g., a 260 microsecond interrupt), and an interrupt occurring on the rising edge of the current limit signal iLIMIT. Of course, other interrupts, timers, and error flags may be included.

At step 715, the software increases the main timer until an interrupt occurs. The interrupt may be the periodic interrupt or an interrupt due to the current limit signal iLIMIT. Once an interrupt occurs then the software proceeds to perform an interrupt service (step 720).

At step 720, the software performs the interrupt service. In general terms, the software determines the cause of the interrupt and performs necessary actions based on the cause. As shown in Figs. 20a and 20b, if the interrupt is due to a high current (step 725), then the current being conducted through the MOSFETs is too high. When this occurs, the software sets a LIMIT flag to high (step 730). Setting the LIMIT flag to high informs later software modules to limit the amount of time the MOSFETs are on. Limiting the amount of time the MOSFETs are on reduces the amount of power and, consequently, current being conducted through the MOSFETs.

If the interrupt was due to a periodic interrupt (step 725), then the software proceeds to step 735. At step 735, the software samples the iLIMIT signal to determine if the amount of current being transmitted by the MOSFETs is within the desired limit. If the current is within limit, then the software sets the LIMIT flag to low (step 740). If the current is not within limit, then the software proceeds to step 745.

At step 745, the software determines whether the interrupt was a periodic interrupt. If the interrupt was a periodic interrupt, then software proceeds to step 750. Otherwise, the software returns from the interrupt service.

At step 750, the software resets the main timer for counting the next interrupt. At step 760, the software calls a HOTSub subroutine. The HOTSub subroutine checks whether the signal produced by the thermal shut down circuit is high. If the signal is high, then the MOSFETs are generating too much heat signifying that too much power is being generated. If the temperature is too hot, then a HOT counter is increased. If the temperature is satisfactory, then the HOT counter is decreased. If the HOT counter reaches a maximum count (e.g., fifteen), then the OUTPUT flag is set to low and the ERR flag is set to high. Setting the OUTPUT flag to low prevents gating of the MOSFETs (discussed below) and the ERR flag informs the processor a possible error is occurring. In addition a display may be used to inform the operator that the generator is too hot. The HOT counter includes a counting range (e.g., between zero and fifteen). Thus, the HOT counter allows the power circuitry 135 to generate some heat. But if too much heat is being generated for too long of a period of time, then the microprocessor U7 prevents electricity from being generated.

At step 765, the software determines whether the OUTPUT flag is set to high. If the OUTPUT flag is set to high, then the software has the microprocessor U7 generate the gating signals GATE1a, GATE1b, GATE2a, and GATE2b for controlling the bridge circuit 540 (step 770). The gating signals control the first and second drivers U4 and U5, which drive the bridge circuit 540. The gating signals are set by the software depending on the results of the PWSub subroutine (discussed below). In general, the software controls the gating of the microprocessor U7 based on the sensed bus voltage. The microprocessor U7 determines the pulse width PWM of the 120-VRMS, 60-Hz signal. If the OUTPUT flag is low (step 765), then the microprocessor U7 does not generate gating signals and the generator does not generate the 120-VRMS, 60-Hz signal (step 775).

At step 778, the software calls a DCSub subroutine, a VPWSub subroutine and a VOUTSub subroutine. The DCSub subroutine calculates the value of the DC bus voltage sensed by the voltage feedback circuit 580. The VPWSub subroutine determines the average value that each MOSFET is on. Based on the average value, the pulse width may be calculated. The VOUTSub subroutine calculates the RMS voltage being generated by the power circuitry 135. The RMS voltage is calculated using the sensed DC bus voltage and the calculated pulse width. For example, the RMS voltage may be calculated using a

sum of squares calculation. If the RMS voltage is too high or too low, the software can adjust the gating signals. In addition, if the voltage is less than 90 VRMS for thirty continuous seconds, then the OUTPUT flag is set to low and the ERR flag is set to high. Similarly, if the voltage is less than 50 VRMS for two continuous seconds, then the  
5 OUTPUT flag is set to low and the ERR flag is set to high.

At step 780, the software determines whether sixty-four interrupts have occurred. If sixty-four interrupts have occurred, then the software performs an ONOFFSub subroutine, a BLADESub subroutine, and a PWSub subroutine (step 785). These subroutines do not need to be performed every interrupt. Of course, sixty-four is an  
10 arbitrary number and other counters may be used. If sixty-four interrupts have not occurred (step 780), then the software increases the interrupt counter (step 790) and returns from the interrupt service.

The ONOFFSub subroutine determines whether the on/off switch for generating the 120-VRMS, 60-Hz signal is on. If the on/off switch is off then it sets the ERR flag to  
15 low. Thus, the user has to "reset" the generator 120. For example, when the engine 110 first starts combusting, the generator 120 does not initially start generating power and accidentally cause damage to an attached load. The operator must turn the generator off and then on before the system will start generating. In addition, the software determines whether an initial DC bus voltage is greater than 120 VDC. If the DC bus voltage is  
20 greater than 120 VDC, then the software sets the OUTPUT flag to high. Thus, before the first power circuitry 450 generates an output, the DC bus voltage must be at least 120 VDC. Of course, other voltages may be used.

The BLADESub subroutine determines whether either the blade signal or the interrupt signal is set to high. If either are high, then the ERR flag is set to high and the  
25 output flag is set to low. For example, if the generator is mounted on a lawnmower, then the operator cannot have the blade on and generate the 120-VRMS, 60-Hz signal at the same time. Similarly, for other vehicles, other interrupts may be used.

The PWSub subroutine uses the values calculated by the VOUTSub, VPWSub and DCSub subroutine to determine which gate signals should be active for driving the bridge

circuit. Once the calculation is performed, the software resets the periodic interrupt count (step 795) and returns from the interrupt to step 715 (Fig. 19).

While multiple embodiments of a small engine vehicle 100 including a generator 120 have been discussed above, additional embodiments are discussed below and with reference to Figs. 21-25. Figs. 21-25 electrically show a generator 1000 capable of being used with the vehicle 100. The generator 1000 includes a flywheel-rotor apparatus (e.g., apparatus 125), a stator, a power circuitry 1002, and an electrical outlet 140.

In the embodiments below, the stator includes a stator core that is substantially similar to the stator core 276 (Fig. 6). However, in other embodiments, the generator 1000 includes different stator cores. Wires 1005, 1010 and 1015 are disposed on the stator core 276 in a three-phase arrangement or connection. Unless specified otherwise, for the winding arrangements herein, the wires 1005, 1010, 1015 are wound (e.g., by machinery or hand) on the core in a wye arrangement. The wires 1005, 1010 and 1015 are wound such that ends 1020, 1025 and 1030 are electrically connected together (e.g., by soldering), and ends 1035, 1040 and 1045 exit the stator core 276. For simplicity, ends 1020-1045 are only numbered in Fig. 21.

For the embodiment shown in Fig. 21, the stator core also receives wire 1050, which is placed on the core 276 in a single-phase arrangement such that ends 1055 and 1060 exit the core 276. The wires 1005A, 1010A and 1015A generate a high-voltage, three-phase alternating current, and the wire 1050 generates a low-voltage, single-phase alternating current. In some embodiments, the high-voltage, three-phase alternating current is greater than approximately 200 V peak-to-peak, and the low-voltage, single-phase alternating current is less than approximately 50 V peak-to-peak. It should be understood that the terms "high-voltage" and "low-voltage" are used for simplifying the description. Other terms may be used (e.g., "first," "second," etc.).

In one embodiment, the wires 1005A, 1010A, 1015A and 1050 are wound on the teeth of the stator core 276 such that the wire 1050 are electrically isolated from wires 1005A, 1010A and 1015A. That is, similar to Fig. 9, if the teeth are numbered 1 to (x), the wires 1005A, 1010A and 1015A are wound onto the teeth numbered from 1 to (x - n), and

the wire 1050 is wound onto the teeth numbered  $(x - n + 1)$  to  $(x)$ . By isolating the wire 1050 from wires 1005A, 1010A and 1015A, the wire 1050 receives less undesirable noise.

In another embodiment, the wires 1005A, 1010A, 1015A are wound onto each of the teeth, and the wire 1050 is wound onto one or more teeth. For example, the wires  
5 1005A, 1010A, 1015A are first wound onto the teeth numbered from 1 to  $(x)$  in a three-phase arrangement, and the wire 1050 is then wound over the wires 1005A, 1010A, 1015A in a single-phase arrangement. As compared to the previous embodiment, disposing the three-phase connection onto all of the teeth results in greater power being generated in the three-phase arrangement.

10 Referring again to Fig. 21, the generator 1000 includes power circuitry 1002. For the embodiment shown in Fig. 21, the power circuitry includes a first power circuitry 1065 that is substantially similar to the circuitry shown in Figs. 12-18. Specifically, the ends 1035, 1040 and 1045 are electrically connected to W3, W4 and W9 (Fig. 13). For other  
15 embodiments, other circuit arrangements may be used in place of the circuitry shown in Figs. 12-18. The first power circuitry 1065 receives the high-voltage, three-phase current and controllably generates a single-phase, alternating current having a voltage between 90 VRMS and 135 VRMS, and having a frequency of 50 or 60 Hz. In one preferred embodiment, the voltage is approximately 120 VRMS, and the frequency is approximately 60 Hz.

20 Referring again to Fig. 21, the power circuitry 1002 includes a second power circuitry 1070. Similar to the single-phase embodiment described above, the ends 1055 and 1060 are connected to the second power circuitry 1070 for controllably generating a direct current. The direct current is preferably less than 50 VDC and, in one preferred embodiment, the direct current is approximately 12 VDC. The direct current is provided  
25 to the vehicle and may be used for charging a battery or for the engine-ignition system. For other embodiments, the direct current is provided to the operator as a DC power source.

In one embodiment, the second power circuitry 1070 includes a voltage regulator 1075. A suitable voltage regulator capable of being used with the invention is available  
30 from Tympanium Corporation of Malden, Massachusetts. Of course, other elements may

be added to the second power circuitry 1070. Additionally, while the first and second power circuitries 1065 and 1070 are shown separately, the circuitries 1065 and 1070 may be interconnected as one circuit.

For the embodiments shown in Figs. 22 and 23, the power circuitry 1002 includes the first power circuitry 1065 and a second power circuitry 1080 or 1085. The first power circuitry 1065 is substantially similar to the circuitry shown in Figs. 12-18. The first power circuitry 1065 receives the high-voltage, three-phase current, and controllably generates a single-phase, alternating current having a voltage between 90 VRMS and 135 VRMS. The second power circuitry 1080 or 1085 includes at least two connections electrically connected to the wires 1005A, 1010A and 1015A. At least one of the connections is a tap off of one of the phases. As used herein, the term "tap" means a connection made at some intermediate point in a winding.

With specific reference to Fig. 22, the second power circuitry 1080 includes two connections 1085 and 1090 interconnected with wire 1005A. The connection 1085 is interconnected to the end of the wire 1005A, and the connection 1090 is a tap off of the wire 1005A. In other embodiments, both connections 1085 and 1090 are taps off of the wire 1005A, or the connections 1085 and 1090 are interconnected to one of the other wires 1010A or 1015A. Similar to Fig. 21 and in one embodiment, the second power circuitry 1080 includes a voltage regulator 1075. The regulator 1075 receives the single-phase alternating current and produces a direct current less than 50 VDC (e.g., 12 VDC).

With specific reference to Fig. 23, the second power circuitry 1085 includes three connections 1095, 1100 and 1105 interconnected with the wires 1005A, 1010A and 1015A. Each connection 1095, 1100 and 1105 is tapped off of one of the wires 1005A, 1010A and 1015A, respectively. The second power circuitry 1085 receives a second three-phase, alternating current, which has a voltage less than the first three-phase alternating current provided to the first power circuitry 1065, and generates a direct current having a voltage less than 50 VDC (e.g., approximately 12 VDC). The second power circuitry 1085 includes a three-phase bridge 1110 and a voltage regulator 1115. The three-phase bridge 1110 may be incorporated with the voltage regulator 1115. In some circumstances, the embodiment shown in Fig. 23 may be preferred over Fig. 22. For

example, the embodiment shown in Fig. 23 has symmetrical taps, allowing a machine to more readily wind the arrangement shown in Fig. 23.

For the embodiments shown in Figs. 24 and 25, the power circuitry 1002 includes a first power circuitry 1125 and a second power circuitry 1130 or 1135. The first power circuitry 1125 receives a three-phase alternating current and generates a single-phase alternating current. For the first power circuitry 1125, the three-phase alternating current is less than the single-phase alternating current and, in one embodiment, is less than 50 V peak-to-peak. The single-phase alternating current produced by the first power circuitry 1125 includes a voltage between 90 and 135 VRMS, or a voltage between 190 and 250 VRMS. Additionally, the single-phase alternating current includes a frequency of 50 or 60 Hz. The first power circuitry 1125 includes circuit elements that increase the incoming voltage and that allow for the higher voltage range (i.e., the 190-250 VRMS rating). This allows the vehicle 100 to provide emergency power to a distribution box for a house. In the embodiments shown, the first power circuitry 1125 includes a three-phase inverter 1140 such as a CHEROKEE™ TS-1000 brand inverter available from NoOutage.Com LLC of Owings, MD. Of course, other components or circuitry may be included in the first power circuitry 1125.

The second power circuitry 1130 or 1135 includes at least two connections interconnected to the plurality of wires 1005B, 1010B, and 1015B. For the embodiment shown in Fig. 24, the second power circuitry 1130 includes first and second connections 1145 and 1150 electrically connected at ends 1020 and 1025. The second power circuitry 1130 receives a single-phase alternating current and produces a direct current less than 50 VDC (e.g., 12 VDC). In the embodiment shown in Fig. 24, the second power circuitry 1130 includes a voltage regulator 1155. Of course, other components or circuitry may be included in the second power circuitry 1130. It is also envisioned that, in some embodiments, the second power circuitry 1130 is interconnected with the first power circuitry 1125.

With specific reference to Fig. 25, the second power circuitry 1135 includes first, second and third connections 1160, 1165, and 1170 connected at ends 1035, 1040, and 1045, respectively. The second power circuitry 1135 receives a three-phase alternating

current and produces a direct current less than 50 VDC (e.g., 12 VDC). In the embodiment shown in Fig. 25, the second power circuitry includes a three-phase bridge 1175 and a voltage regulator 1180. Of course, other components or circuitry may be included in the second power circuitry 1135. It is also envisioned that, in some  
5 embodiments, the second power circuitry 1135 is interconnected with the first power circuitry 1125.

As can be seen from the above, the present invention provides a vehicle including a generator. Various features and advantages of the invention are set forth in the following claims.

11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
2184  
2185  
2186  
2187  
2188  
2189  
2190  
2191  
2192  
2193  
2194  
2195  
2196  
2197  
2198  
2199  
2200  
2201  
2202  
2203  
2204  
2205